

BMB01

Remote I/O Expansion Unit



The BMB01 is an input and output control port (I/O) expander for ASL's range of DSP Audio Routers. Each DSP Audio Router supporting the connection of up to 9 remote BMB01 units, connected by a multi-drop RS485 serial interface.

Each BMB01 unit provides the following inputs and outputs to extend the control and interfacing capability of the router:

- 12 analogue inputs
- 12 digital (opto-isolated) inputs
- 12 digital (open collector) outputs

These input and output control ports may be used for functions such as: Program Selection, Volume Control, Fault Input, Routing Control, Routing Reset Input, External Fault Input, and Busy Output.

The BMB01 is housed in a DIN-rail mountable enclosure suitable for use either within a central equipment rack or remotely, at distances of up to 1km from the Router.

For further details please refer to the BMB01 product manual, the Audio Router manual, or visit www.asl-control.co.uk.

Specification

General

Supply voltage range.....18 – 40V DC
Current consumption 70mA @ 24V DC supply
Open collector maximum rated current..... 350mA
Open collector maximum voltage..... 60V
Analogue input voltage range..... 0 – 5V (nominal) 24V max without physical damage
Digital input voltage range..... 12 – 48V

Dimensions and Weight

Dimensions (H x W x D).....105mm x 156mm x 58mm
Weight 300g

Environmental

Temperature (storage and operating) –5°C to +50°C
Humidity range0% to 93% Non-condensing

Compatibility

Audio RoutersVAR Range, IPAM Range and VIPEDIA-12 Range



This equipment is designed and manufactured to conform to the following EU Directives:

Electromagnetic Compatibility (EMC): 2014/30/EU

Low Voltage: 2014/35/EU

Restriction of Hazardous Substances (RoHS): 2011/65/EU

Manufacturer

Application Solutions (Safety and Security) Limited

Unit 17 Cliffe Industrial Estate

Lewes - East Sussex

BN8 6JL - UK

Tel: +44(0)1273 405411

Fax: +44(0)1273 405415

www.asl-control.co.uk



Assessed to ISO 9001
LPCB Cert No: 1043QMS

All rights reserved.

Information contained in this document is believed to be accurate, however no representation or warranty is given and Application Solutions (Safety and Security) Limited assumes no liability with respect to the accuracy of such information.